

# Delock Converter M.2 2280 Key B+M male to 8 x SATA

## Description

This converter by Delock expands the system by **8 SATA ports**. Different devices such as SSDs, hard drives, DVD-drives etc. can be connected to the converter.



**Item no. 64211**

EAN: 4043619642113

Country of origin: China

Package: Box

## Technical details

- Connectors:
  - 1 x M.2 key B+M male
  - 2 x SFF-8087 female
- Connection cables:
  - 1 x SFF-8087 male
  - 4 x SATA 6 Gb/s 7 pin receptacle
- Chipset: JMicron JMB585, JMB575
- Interface: PCIe
- Form factor: M.2 2280
- Suitable for M.2 slot with key M or B based on PCIe
- 8 x LED indicator for power and access
- Data transfer rate up to 6 Gb/s
- Supports Native Command Queuing (NCQ)
- Supports S.M.A.R.T.
- Supports TRIM
- Supports DevSleep
- Hot Swap
- Bootable (CN1)
- Dimensions (LxWxH): ca. 80 x 22 x 21 mm

---

## System requirements

- Linux Kernel 5.13 or above
- Windows 8.1/8.1-64/10/10-64/11
- Windows Server 2019
- A free M.2 key M or key B slot


---

## Package content

- Converter
- 2 x Cable SFF-8087 male to 4 x SATA receptacle, length ca. 1 m
- 1 x screw
- User manual

---

## Images



## General

Supported operating system:	Windows 10 32-Bit Windows 10 64-Bit Windows 8.1 32-Bit Windows 8.1 64-Bit Windows Server 2019 Windows 11 Linux Kernel 5.13 or above
LED indicator:	8 x
Slot:	PCIe

## Interface

Connector 1:	1 x M.2 key B+M male
Connector 2:	8 x SATA 6 Gb/s 7 pin receptacle

## Technical characteristics

Chipset:	JMicron JMB585 JMicron JMB575
Data transfer rate:	6 Gb/s